


# Index

1. Important information	4
2. Introduction and required tools	
3. Pairing	
Powering	11
Connecting Shifters	13
Connecting Shifters Disc Brake	15
4. Drivetrain Parts	18
Part Names	18
Using the Wiring tool	19
How to Wire	20
Lever Installation	21
Brake Cable Installation	22
Reach adjustments	23
Front Derailleur Installation	24
Rear Derailleur Installation	26
Battery Installation	27
Chain Installation	28
5. How to operate	32
Gear position control	32
6. Usage and adjustments	34
Rear Derailleur Adjustment	34
Front Derailleur Adjustment	
Limit Screw Adjustment	39
B-tension Screw Adjustment	40
7. Battery	42
Names of parts	42
Battery Diagnostic	43
How to Charge	44
8. Disc Brake Installation	50
9. Diagnostic	65



Congratulations on your Full Speed Ahead product. Please read these instructions and follow them for correct use. Failure to follow the warnings and instructions could result in damage to product not covered under warranty, damage to bicycle; or cause an accident resulting in injury or death. Since specific tools and experience are necessary for proper installation, it is recommended that the product be installed by a qualified bicycle technician. FSA assumes no responsibility for damages or injury related to improperly installed components.

### Important Information

**▲** CAUTION

Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.

If your device endures electrostatic discharge, it may automatically reboot and disconnect current wireless transmission. You will need to manually reset the wireless connection when this happens.

Use your device in temperature between  $-5^{\circ}$ C  $\sim 40^{\circ}$ C. Exposing your device to extremely low or high temperatures may result in damage, malfunction, or even explosion.

## **FCC Compliance Statement**

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1)This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- -Reorient or relocate the receiving antenna.
- —Increase the separation between the equipment and receiver.
- —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- —Consult the dealer or an experienced radio/TV technician for help.

## **FCC RF Exposure Information**

This device is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the Federal Communications Commission for an uncontrolled environment.

ISED Compliance Statement

This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions:

- (1) This device may not cause interference; and
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence.

L'exploitation est autorisée aux deux conditions suivantes:

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement."

CAN ICES-3(B)/NMB-3(B)

### ISED RF Exposure Information

This equipment complies with Innovation, Science and Economic Development Canada RSS-102 RF exposure limits set forth for an uncontrolled environment.

### ISED Informations sur l'exposition RF

Cet équipement est conforme aux limites d'exposition RF RSS-102 d'Innovation, Sciences et Développement économique Canada établies pour un environnement non contrôlé.

### **CE Compliance Statement**

### Maximum radio-frequency power transmitted in the frequency bands:

Model: FD-ED-8400

Bluetooth LE, 2400MHz~2483.5MHz: -5.8 dBm (e.i.r.p.)

ANT+, 2402MHz~2480MHz: -4.8 dBm (e.i.r.p.)

Model: SF-ED-8400

Bluetooth LE, 2400MHz~2483.5MHz: -4.1 dBm (e.i.r.p.)

ANT+, 2402MHz~2480MHz: -5.5 dBm (e.i.r.p.)

### **CE RF Exposure Information**

This device meets the EU requirements and the International Commission on Non-Ionizing Radiation Protection (ICNIRP) on the limitation of exposure of the general public to electromagnetic fields by way of health protection.



### Waste Electrical and Electronic Equipment (WEEE)

This symbol means that according to local laws and regulations your product and/or its battery shall be disposed of separately from household waste. When this product reaches its end of life, take it to a collection point designated by local authorities. Proper recycling of your product will protect human health and the environment.

Hereby, FSA srl declares that the radio equipment type [FD-ED-8400 and SF-ED-8400] is in compliance with Directive 2014/53/EU.

The full text of the EU declaration of conformity is available at the following internet address: http://www.fullspeedahead.com/en/support/library/documentation

### NCC 警語

本電池如果更換不正確會有爆炸的危險,請依製造商説明書處理用過之電池

### ₩ 廢電池請回收

經型式認證合格之低功率射頻電機,非經許可,公司、商號或使用者均不得擅自變更頻率、加大功率或 變更原設計之特性及功能。低功率射頻電機之使用不得影響飛航安全及干擾合法通信;經發現有干擾現 象時,應立即停用,並改善至無干擾時方得繼續使用。

前項合法通信,指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

## **Battery Warning**

### Battery

- 1. Be sure to use only with an FSA charger and follow charging instructions.
- 2. Do not crush and/or do not puncture the battery.
- 3. If the battery pack is stored for a long time, the battery pack's storage should be 7.8V~8.0V.
- 4. Charging

### **Charging Current**

The charging current should be less than the maximum charge current specified in the Product Specification. Charging with a higher current than the recommended value may cause damage to cell/battery pack's electrical, mechanical, and safety performance and could lead to heat generation or leakage.

### **Charging Temperature**

The cell should be charged within a 0°C~45°C (32°-113°F) range in the Product Specification.

### **Prohibition of Reverse Charging**

Reverse charging is prohibited. The cell/battery pack should be connected correctly. The polarity has to be confirmed before wiring. In case the cell/battery pack is connected improperly, the cell/battery pack cannot be charged. Likewise, reverse charging may cause damage to the cell/battery pack which may lead to degradation of the cell/battery pack performance, affect the cell/battery pack safety and could cause heat generation or leakage.

### 5. Discharging

### **Discharging Current**

The cell should be discharged at less than the maximum discharge current specified in the Product Specification. A high discharging current may reduce the discharging capacity significantly or cause over-heating.

### Discharging Temperature

The cell should be discharged within a -20°C~60°C (-4°-140°F) range specified in the Product Specification.

#### Over-Discharging

It should be noted that the cell/battery pack would be in an over-discharged state by its selfdischarge characteristics if the cell/battery pack has not been used for long time. In order to prevent over-discharging, the (individual) cell should be charged periodically to maintain between 7.8V and 8.0V Over-discharging may cause loss of cell/battery pack performance, characteristics, or battery functions.

### 6. Storage

The cell/battery pack should be stored within a -10°C~45°C (14°-113°F) range.

### 7. Long Time Storage

If the battery pack is stored for a long time, the battery pack's storage should be 7.8V~8.0V.

#### Instructions for "long term storage":

- a. Long-term storage can accelerate battery self-discharge and lead to the deactivation of the batteries.
- To minimize the deactivation, store battery packs in a temperature range of -10°C~45°C (14°-113°F).
- b. When charging for the first time after long-term storage, deactivation of the packs may have led to decreased capacity.
- To recover the packs to original performance, repeat several cycles of fully charging and discharging.
- c. When storing the pack for more than 6 months, please charge at least once every 6 months to prevent leakage and deterioration in performance due to self-discharging.

Do not drop, hit or bend the battery body.

### Battery electrolyte is harmful

The battery should not have any electrolyte liquid visibly flowing. In case electrolyte comes into contact with the skin or eyes, flush/wash the electrolyte immediately with fresh water and immediately seek medical attention.

### Prohibition of dumping of cells into fire

Never incinerate nor dispose of the cells in fire. This may cause a dangerous explosion and is prohibited.

### Prohibition of cells immersion into liquid such as water

The cells should never be soaked with liquids such as fresh water, seawater, or drinks such as soft drinks, juices, coffee, etc.

### Battery cells replacement

The battery replacement shall be done only by either the battery cell supplier or device supplier and never be done by the user.

### Prohibition of use of damaged cells

The cells might become damaged during shipping by shock. If any abnormal features of the cells are found - such as damage to the plastic envelope of the cell, deformation of the cell package, smelling of electrolyte, electrolyte leakage or other abnormal appearance, the cells should not be used.

The cells with a smell of the electrolyte or a leakage shall be placed away from fire to avoid explosion.




### Introduction

Congratulations on your Full Speed Ahead product. Please read these instructions and follow them for correct use. Failure to follow the warnings and instructions could result in damage to product not covered under warranty, damage to bicycle: or cause an accident resulting in injury or death. Since specific tools and experience are necessary for proper installation, it is recommended that the product be installed by a qualified bicycle technician. FSA assumes no responsibility for damages or injury related to improperly installed components.

### Required Tools and supplies



FSA recommends installation of WE Drivetrain to be performed by a highly experienced bicycle mechanic.







Needle nose pliers



Brake fluid



Bleed block



Hydraulic hose cutting tool



Hydraulic hose barb insertion tool



Isopropyl or Denatured Alcohol



Clean, Lint-Free Rags



Safety Glasses and Nitrile Gloves




Shift cable for hose routing



## **POWERING**

### Power ON




TIPS

Release the power button. Push each shift button once to activate them.

### **POWERING**


### **Power OFF**



TIPS

WE will also go in to Stand-By mode, and turn off automatically after a period of inactivity. Those intervals are customizable in the WE Dashboard Software.


# **Connecting shifters**



**TIPS** 

If you have pressed the shifting paddle too recently before the pairing button it will not enter pairing mode. You need at least 30s until you can enter pairing mode.


# **Connecting shifters**



TIPS

Repeat the above process for the other sifter.


# **Connecting Shifters Disc Brake**



TIPS

If you have pressed the shifting paddle too recently before the pairing button it will not enter pairing mode. You need at least 30s until you can enter pairing mode.

# **Connecting Shifters Disc Brake**




**TIPS** 

Repeat the above process for the other sifter.



### **Part Names**

FSA K-Force WE is an electronic hybrid drivetrain. It is defined as hybrid because is not completely wireless. Indeed, there are no wires from shifters to derailleurs but the communication between the two derailleurs is still achieved using wires. The different parts of the drivetrain will be explained in this section.



#### Levers:

Shifters wirelessly communicate with derailleurs. They have their own coin cell batteries (CR2032), located inside the housing.

#### Battery:

The main battery is placed into the seatpost and provides power to the two derailleurs through two wires.

### Front derailleur:

Maximum tooth differential up to 16T, compatible with K-Force WE crankset.


### Rear derailleur:

Max sprocket up to 32T, compatible with K-Force WE cassette.


### Wires:

Two internally routed wires, one longer and one shorter, connect front and rear derailleurs to the battery.


# **Using the Wiring tool**




### How to wire




## **Lever Installation**




# **Brake Cable Installation**




# **Reach Adjustments**




# **Front Derailleur Installation**




## **Front Derailleur Installation**




### **Rear Derailleur Installation**



# **Battery Installation**




## **Chain Installation**



### **Chain Installation**

### Chain lock




TIPS

Make sure Drive Link snaps in to locked position before use.

## **Chain Installation**

### Unlock the chain





TIPS

Drive Link cannot be reused if removed. Use a new Drive Link to reassemble.




# **Gear position control**







# Rear Derailleur Adjustment



# Rear Derailleur Adjustment




## Front Derailleur Adjustment




#### IIPS

- 1.Enter the front derailleur adjustment mode (By factory default is the left one but you can change it in the WE Dashboard Software).
- 2.Rotate the crank when pressing the front derailleur button. The front derailleur will shift when the button is pressed, so make sure the chain can change rings if required.


## Front Derailleur Adjustment



## Front Derailleur Adjustment




### **Limit Screw Adjustment**



TIPS

Do not tighten the limit screw against its stop. Tightening may result in reduced performance or damage to RD internals.


### **B-tension Screw Adjustment**




- **TIPS**
- 1. B-tension screw adjustment must be set after all derailleur and limit screw adjustments. B-tension screw adjustment optimizes the distance between the upper jockey pulley and cassette cogs.
- 2. For optimal shifting, move the pulley as near as possible to the cog without making contact.
- 3. When B-tension is set, double check RD functionality and adjustment. If RD need adjustment, repeat the adjustment process.



# Names of parts




### **Battery Diagnostic**



WE uses three batteries. The main battery powers the front and rear derailleurs.


Each shifter is powered by a CR2032 coin cell battery.



#### Main battery

When WE is on, the LED 1 on the main control unit will blink every 3 seconds (customizable by We Dashboard App).

Main battery level is indicated by the following LED color codes.



#### Shifter battery

The shift batteries are CR2032 coin cell batteries and are not rechargeable. When the battery level is low, they must be replaced. It is not necessary to replace both batteries at the same time if they are not both showing a low charge.


Each time a shift button is pressed a corresponding LED will blink on the main controller.

LED 1 blinks for the right shifter, LED 2 blinks for the left shifter. The color of the LED will be related to the level of the battery.

#### TIPS

LED Color	Battery Level	Action	
	77-100%	Battery level is high, no action necessary.	
	23-77%	Battery level is OK.	
$\bigcirc$	0-23%	Replace battery as soon as possible.	
$\bigcirc$	0%	Replace battery immediately. The Shifter will stop to work.	


#### Shifter battery replacement



**TIPS** 

Battery LED signal please check 7-2.


### Shifter battery replacement



TIPS

Battery LED signal please check 7-2.


Shifter battery replacement - Disc Brake



TIPS

Battery LED signal please check 7-2.


#### Main battery charging



#### **TIPS**

- 1. Turn WE off before charging the battery.
- 2. Battery LED signal please check 7-2.

#### Main battery charging




The charger light will be red while charging and turn to green at full charge.


#### TIPS


- 1. Turn WE off before charging the battery.
- 2. Battery LED signal please check 7-2.








4	Install provided FSA bleed block between caliper pistons.	**
5	Cut brake hose at caliper end. Leaving 25mm or 1" of exposed hose from the top of the compression nut.	
6	Install provided hose caps (2) on lever side of hose ends.	

























TIPS


Repeat steps 1-32 for both calipers.





Reach Adjustment - Disc Brake

neach Aujustinent Disc Blake						
1	Expose the reach adjustment screw by pulling back the hood.					
2	Adjust reach by loosening or tightening the screw with a 2.5mm hex wrench.	2.5				
3	Increase the reach by turning the screw counter-clockwise.  Decrease the reach by turning the screw clockwise.					



# Diagnostic

Action	LED Indication	Issue	Remedy	
	Both LEDs solid red	Front derailleur stall	Check that the derailleur is mounted correctly     Check the SET point	
	Both LEDs solid yellow	Rear derailleur stall	Check that the derailleur is mounted correctly     Check the SET point	
	LED 1 solid green and LED2 solid red	Communication absence between front and rear derailleur	<ul> <li>Check connections of both derailleurs.</li> <li>Check wires for damage</li> </ul>	
	LED 1 solid red and LED 2 solid green	Failed reply from rear derailleur to front derailleur at end of shift. Probable loss of rear derailleur position	<ul> <li>Check the connection of both derailleurs connector.</li> <li>Check the SET point</li> </ul>	